

| Command list : | | | |
|--|--|----------------------------|---|
| Parameter Description | Set up instruction | Query instruction | Instruction Description |
| Server address | SZCS#SERVIP=122.9.115.220#SERVPORT=7711 | CXCS#SERVIP#SERVPORT | You can set the domain name and IP, or you can use the directive IP,122.9.115.220,7711 |
| Second server address | SZCS#SERV2_ADDR=122.0.64.102#SERV2_PORT=7700 | CXCS#SERV2_ADDR#SERV2_PORT | The domain name and IP address can be set. The software must support the dual IP address setting |
| Querying the Status | CXZT | | Reply: Version number +ID+IP+ port +APN+GPS status +GSM signal value and so on, please see comments for details |
| fortified | SF | | Realize vibration alarm |
| removal | CF | | |
| factory data reset | FORMAT | | After the restoration, the APN and IP remain unchanged |
| Disconnect oil current | DY | | To ensure vehicle safety, the terminal should be powered off only when the GPS is in effective positioning state and the vehicle speed is less than 20KM/H or the vehicle is stationary. Cancel speed SMS command: SZCS#SOURCE_OFF_TYPE=1 |
| Restore oil power | KY | | |
| Rest Enter hibernation time | SZCS#SLEEPT=3 | CXCS#SLEEPT | Unit minute, set no vibration and ACC off, enter hibernation wait time |
| Device restart | CQ | | |
| APN Settings | SZCS#APN=cmnet#USERPPP=666#PWPPP=123 | CXCS#APN#USERPPP#PWPPP | 666 is the account number and 123 is the password. If there is no account number and password, set SZCS#APN=cmnet |
| Wake up position reporting interval | SZCS#FREQ=30 | CXCS#FREQ | The unit is second. The limit value is greater than 5 |
| Interval for reporting heartbeat packets | SZCS#PULSE=180 | CXCS#PULSE | The unit is second. The value is greater than 60 |
| Time Zone Settings | SZCS#GMT_SET=E0800 | CXCS#GMT_SET | E is East, + time zone, Beijing is East 8 zone, instruction set to SZCS#GMT_SET=E0800 W is West, - time zone, Washington is West 5, command set to |
| 808 protocol sleep upload location | SZCS#ACC_OFF_FREQ=300 | CXCS#ACC_OFF_FREQ | The default value is 300 seconds. After the device is hibernated, heartbeat packets and location data are uploaded |
| ICCID Query | | CXCS#ICCID | This parameter can only be queried but cannot be set |
| Protocol Switching | SZCS#PTL_SEL=0 | CXCS#PTL_SEL | Set the platform protocol,0 is Tianqin, 1 is 808,2 is GT06 (supported by the new version) |
| 808 Protocol version configuration | SZCS#808SEL=0 | CXCS#808SEL | Setting 0 indicates the 2011 version and 1 indicates the 2013 version (default: 2011 version). |

| | | | |
|--|--|--|--|
| | | | |
| | | | |